DUAL ZONE ENERGIZER: MERLIN STEALTH M28



The Merlin Stealth dual zone energizer range provides a powerful, versatile and cost-effective security solution for applications ranging from residential properties to high-security installations where multiple zones are required. Dividing the electric fence into two independent zones makes it easier to identify the specific area affected by a fence fault or attempted tampering. Its intelligent design directs the maximum available energy to the zone that requires it, while ensuring that the combined output of both zones remains within the legally permitted maximum. The energizers can be conveniently controlled using a tag and/or keypad and can be programmed to provide customised security solutions tailored to specific requirements.

Features:

- 6 Joule output energy (dual zone)
- Robust and flexible design for home and commercial security
- Built-in alarm monitors tampering or faults on the high voltage and earth fence wires
- Connectable to armed response radio or GSM module
- Lightning and power surge protection
- Intelligent power-saving technology designed to extend battery life.
- Control the energizer with the easy-to-use tag, included.
- Optional keypad for controlling and programming the energizer. This allows the user to control the energizer remotely, with up to four keypads
- Powered by 240V mains and includes built-in battery for back-up power
- Two built in gate chimes available to provide an audible alert when the gate is opened or closed.

DUAL ZONE ENERGIZER: MERLIN STEALTH M28

NEMTEK Electric Fencing Products

Specifications:

Enclosure size	L370 x W232 x D145mm
Weight	4.8kg excluding battery (7AH) 7.0kg including battery (7AH)
IP rating	IPx4
Operating temperature	-10°C to 50°C
Operating humidity	< 80% non-condensing
Electrical supply voltage	240V
Typical power consumption	27VA (normal operating conditions)
Standby Time	6hrs (fully charged battery)
Energy output	7.6 Joule (500 Ohms load)
Open circuit voltage	9300V

Stock Code	Description
E-M28S/V1	Dual Zone Energizer: Merlin Stealth M28